

Contents: [Dobrica PavlinuÅiÄ 's random unstructured stuff]

- Dobrica PavlinuÅiÄ 's random unstructured stuff (Working configuration)
 - ◆ Dobrica PavlinuÅiÄ 's random unstructured stuff (/etc/ppp/peers/huawei-e220)
 - ◆ Dobrica PavlinuÅiÄ 's random unstructured stuff (/etc/chatscripts/huawei-e220.chat)
- Dobrica PavlinuÅiÄ 's random unstructured stuff (Links)
- Dobrica PavlinuÅiÄ 's random unstructured stuff (Turn off pin)
- Dobrica PavlinuÅiÄ 's random unstructured stuff (libusb driver program)
 - ◆ Dobrica PavlinuÅiÄ 's random unstructured stuff (Compilation)
- Dobrica PavlinuÅiÄ 's random unstructured stuff (hal problem)
- Dobrica PavlinuÅiÄ 's random unstructured stuff (CD image update)
 - ◆ Dobrica PavlinuÅiÄ 's random unstructured stuff (dmesg)
 - ◆ Dobrica PavlinuÅiÄ 's random unstructured stuff (power)
 - ◆ Dobrica PavlinuÅiÄ 's random unstructured stuff (links)
- Dobrica PavlinuÅiÄ 's random unstructured stuff (E171)
- Dobrica PavlinuÅiÄ 's random unstructured stuff (E1752)

Working configuration

(for me at least :-)

/etc/ppp/peers/huawei-e220

```
dpavlin@llin:~$ cat /etc/ppp/peers/huawei-e220
# /etc/ppp/peers/huawei-e220 pppd script
# pppd call huawei-e220

debug
kdebug 3
nodetach
#persist

/dev/ttyUSB0
460800
idle 7200
noipdefault
defaultroute
usepeerdns

connect "/usr/sbin/chat -vf /etc/chatscripts/huawei-e220.chat"

# avoid compression:
noccpx
#nobsdcomp
novj
# t-mobile specific?
#ipcp-restart 8
#ipcp-max-configure 50
#ipcp-accept-local
#ipcp-accept-remote
#ipcp-max-failure 20

lcp-echo-failure 0
lcp-echo-interval 0
```

```
modem
crttscts

require-pap
refuse-chap

show-password
user YOUR_USERNAME@DOMAIN
password YOUR_PASSWORD

passive
```

/etc/chatscripts/huawei-e220.chat

```
dpavlin@llin:~$ cat /etc/chatscripts/huawei-e220.chat
TIMEOUT 3
ABORT BUSY
ABORT 'NO CARRIER'
ABORT VOICE
ABORT 'NO DIALTONE'
ABORT 'NO DIAL TONE'
ABORT 'NO ANSWER'
ABORT DELAYED
"" ATZ
OK ATQ0V1E1S0=0&C1&D2
OK AT+COPS?
OK AT+CGDCONT=1,"ip","carnet.vip.hr"
OK ATDT*99#
CONNECT ""
```

Links

- <http://wwwu.uni-klu.ac.at/agebhard/HuaweiE220/>
- another tutorial: http://ske.sourceforge.net/html/projects/huawei/huawei_tre.html
- interesting compilation of configuration files and stat tool:
<http://oozie.fm.interia.pl/pro/huawei-e220/>
- Ubuntu, GUI: <http://sistematic-portal.carnet.hr/node/335>
- source: <http://www.kanoistika.sk/bobovsky/archiv/umts/>
- ObWikipedia: http://en.wikipedia.org/wiki/Huawei_E220

Turn off pin

```
$ cu -l /dev/ttyUSB0
at+clck="sc",0,"PIN!"
OK
```

libusb driver program

Compilation

Get source from <http://www.kanoistika.sk/bobovsky/archiv/umts/huaweiAktBbo.c>

```
cc huaweiAktBbo.c -o huaweiAktBbo -lusb
```

hal problem

If your modem is restarting like mad, it's a problem with hal.

- http://wiki.archlinux.org/index.php/Huawei_E220

CD image update

Since the device can emulate USB CDROM, I will try to update the image on it to provide a BIOS update image instead of useless (to me) Windows drivers.

dmesg

```
dpavlin@t61p:~$ uname -a
Linux t61p 2.6.30-1-686-bigmem #1 SMP Mon Aug 3 17:32:39 UTC 2009 i686 GNU/Linux
dpavlin@t61p:~$ dmesg
[ 3405.568120] usb 4-1: new full speed USB device using uhci_hcd and address 2
[ 3405.726188] usb 4-1: New USB device found, idVendor=12d1, idProduct=1003
[ 3405.726196] usb 4-1: New USB device strings: Mfr=1, Product=2, SerialNumber=0
[ 3405.726203] usb 4-1: Product: HUAWEI Mobile
[ 3405.726208] usb 4-1: Manufacturer: HUAWEI Technologies
[ 3405.726384] usb 4-1: configuration #1 chosen from 1 choice
[ 3405.792930] Initializing USB Mass Storage driver...
[ 3405.796244] usb-storage: probe of 4-1:1.0 failed with error -1
[ 3405.796289] usbcore: registered new interface driver usb-storage[ 3405.796296] USB Mass Storage
[ 3405.952077] usb 4-1: USB disconnect, address 2
[ 3407.432107] usb 4-1: new full speed USB device using uhci_hcd and address 3
[ 3407.590171] usb 4-1: New USB device found, idVendor=12d1, idProduct=1003
[ 3407.590180] usb 4-1: New USB device strings: Mfr=1, Product=2, SerialNumber=0
[ 3407.590187] usb 4-1: Product: HUAWEI Mobile
[ 3407.590192] usb 4-1: Manufacturer: HUAWEI Technologies
[ 3407.590373] usb 4-1: configuration #1 chosen from 1 choice
[ 3407.603280] usb-storage: probe of 4-1:1.2 failed with error -1[ 3407.650695] usbcore: register
[ 3407.650725] USB Serial support registered for generic
[ 3407.650819] usbcore: registered new interface driver usbserial_generic
[ 3407.650824] usbserial: USB Serial Driver core
[ 3407.663176] USB Serial support registered for GSM modem (1-port)
[ 3407.663293] option 4-1:1.0: GSM modem (1-port) converter detected
[ 3407.663458] usb 4-1: GSM modem (1-port) converter now attached to ttyUSB0
[ 3407.663478] option 4-1:1.1: GSM modem (1-port) converter detected
[ 3407.663576] usb 4-1: GSM modem (1-port) converter now attached to ttyUSB1
[ 3407.663609] usbcore: registered new interface driver option
[ 3407.663614] option: v0.7.2:USB Driver for GSM modems
```

power

```
root@t61p:~/t61p/usb_modeswitch/usb_modeswitch-1.0.2# lsusb
Bus 004 Device 003: ID 12d1:1003 Huawei Technologies Co., Ltd. E220 HSDPA Modem / E270 HSDPA/HSUPA
Bus 004 Device 001: ID 1d6b:0001 Linux Foundation 1.1 root hub

root@t61p:~/t61p/usb_modeswitch/usb_modeswitch-1.0.2# echo suspend > /sys/bus/usb/devices/4-1/power
root@t61p:~/t61p/usb_modeswitch/usb_modeswitch-1.0.2# dmesg
```

links

- http://www.draisberghof.de/usb_modeswitch/

fetchrss: <http://feeds.delicious.com/v2/rss/dpavlin/e220?count=15>

- There was an error: 500 Can't connect to feeds.delicious.com:80 (Bad hostname 'feeds.delicious.com')

E171

```
Found modem      : E171
Model            : Huawei E171
IMEI            : 354807044078459
Serial NR.      : 4BA5TA10B2706637
Firmware        : 11.126.85.01.143
Compile date / time : Jun 21 2010 20:27:27
Dashboard version : UTPS11.300.05.15.143_MAC11.301.09.01.143
Chipset         : Qualcomm MSM6290
Voice feature    : disabled
SIM Lock status  : unlocked
Wrong codes entered : 0 (unlock attempts left : 10)
```

E1752

```
Found modem      : E1752
Model            : Huawei E1752
IMEI            : 353145034241600
Serial NR.      : 047NAA19A1600110
Firmware        : 11.126.13.00.00
Compile date / time : Jul 05 2010 10:16:42
Dashboard version : UTPS11.300.05.22.56_MAC11.300.08.19.56
Chipset         : Qualcomm MSM6290
Voice feature    : disabled
SIM Lock status  : unlocked
Wrong codes entered : 0 (unlock attempts left : 10)
```

```
AT^CVOICE=0 Enable Voice
AT^CVOICE=1 Disable Voice
```

AT^CVOICE=? Check status

=====

AT^U2DIAG=0 â switch the device in modem mode only

AT^U2DIAG=1 â device in modem mode + CD-ROM

AT^U2DIAG=255 â modem mode + CD-ROM + Card Reader

AT^U2DIAG=256 â modem mode + Card Reader