

<https://tasmota.github.io/docs/devices/Nedis-WIFIP310FWT/>

https://templates.blakadder.com/nedis_WIFIP310FWT.html

Description: 3 port AC outlets (European Schucko Type F) + 4 USB power outlets

Power input: 16 A - 230 VAC

Max. Power: 3680 W

Power output: USB: 5 VDC /2.4 A each

mapping

GPIO #	Component
GPIO00	None
GPIO01	Led1i
GPIO02	None
GPIO03	Button1
GPIO04	Relay2
GPIO05	Relay1
GPIO09	None
GPIO10	None
GPIO12	None
GPIO13	Relay3
GPIO14	Relay4
GPIO15	None
GPIO16	None
FLAG	Analog

Template:

```
{"NAME": "Nedis WIFIP310", "GPIO": [0, 56, 0, 17, 22, 21, 0, 0, 0, 23, 24, 0, 0], "FLAG": 1, "BASE": 18}
```

new template for version 9

```
IO": [0, 320, 0, 32, 225, 224, 0, 0, 0, 226, 227, 0, 0, 4704], "FLAG": 0, "BASE": 18}
```